

Specifications

BA-99 Professional AV Amplifier

Max Rated Output Power	230W + 230W + 150W at 8 Ω
Music Frequency Response	10 - 40,000Hz ± 3dB
Microphone frequency Response	20 - 25,000Hz ± 3dB
Total Harmonic Distortion	1kHz, 8Ω, 0.03% at 50W
Music Tone control	Treble ± 10dB (10kHz) Bass ± 10dB (100Hz)
Microphone Tone Control	Treble ± 10dB (10kHz) Mid ± 5dB (2kHz) Bass ± 10dB (100Hz)
Music Master Vol	Manual Vol, (Remote control)
Mic Master Vol.	Manual Vol, (Remote control)
Mic Vol.	Mic 1/A, 2/B, 3MC
Key Control Range	11steps ± 2.5pitch
Key Control Switch	Manual Sw, (Remote control)
F. B. EX	3 Mode (Avoid Whistle)
F. B. EX Switch	Manual Sw, (Remote control)
Input Select	BGM,VCR,DVD,AUX
External Audio Inputs	BGM,VCR,DVD,AUX
Visual Inputs	BGM,VCR,DVD,AUX
Visual Outputs	4 Tarminals
Digital Control (From PC)	RS232
Microphone Inputs	Front (1.2.3), Rear (A,B)
Music Effector Terminals	Send and Return
Mic Effector Jack	Send and Return
Pre-Outputs	L, R, Visual
Sub W. Output	Subwoofer Out
Speaker Terminals	L, R
Speaker Terminals	Center Speaker
Echo Level Control	Manual Vol, (Remote control)
Echo Control	Repeat/Delay
Echo Reverb control	Time/Level (Remote control)
OK. Mode	L+R, L+R+C (Remote control)
Music Auto Level Control	(Remote control)
Center Chanel Level Control	(Remote control)
Sub-Woofer output Level Control	(Remote control)
Pre-Amp Input Jack	L, R
Ext. Remote Sensor	1
Mute	On / Off (Remote control)
Power Consumption	870W
Dimension (W x H x D)	420 x 154 x 364 mm
Weight	12.5kg



BIK CO.,LTD.

3-34 YANAKA-CHO, KOSHIGAYA-SHI,
SAITAMA-KEN 343-0856 JAPAN

TEL. +81-48-969-6533 FAX. +81-48-969-6556

URL. <http://www.bik-audio.com>

Email. best-sound@bik-coltd.jp